

Input Data (Master → CC-Link remote device)

Remote Input (RX)

Signal name	I/O port No.			Note
	2 stations occupied 64 points	3 stations occupied 96 points	4 stations occupied 128 points	
Step stop (all tasks)	512	512	512	
(Reserved)	513	513	513	Not available
Halt (all tasks)	514	514	514	
Strobe signal	515	515	515	
Skip interrupt	516	516	516	
(-)	517	517	517	Not available
(-)	518	518	518	Not available
Command and data odd parity	519	519	519	
Bit 0 in data area 1	520	520	520	
Bit 1 in data area 1	521	521	521	
Bit 2 in data area 1	522	522	522	
Bit 3 in data area 1	523	523	523	
Bit 4 in data area 1	524	524	524	
Bit 5 in data area 1	525	525	525	
Bit 6 in data area 1	526	526	526	
Bit 7 in data area 1	527	527	527	
Bit 0 in data area 2	528	528	528	
Bit 1 in data area 2	529	529	529	
Bit 2 in data area 2	530	530	530	
Bit 3 in data area 2	531	531	531	
Bit 4 in data area 2	532	532	532	
Bit 5 in data area 2	533	533	533	
Bit 6 in data area 2	534	534	534	
Bit 7 in data area 2	535	535	535	
Bit 8 in data area 2	536	536	536	
Bit 9 in data area 2	537	537	537	
Bit 10 in data area 2	538	538	538	
Bit 11 in data area 2	539	539	539	
Bit 12 in data area 2	540	540	540	
Bit 13 in data area 2	541	541	541	
Bit 14 in data area 2	542	542	542	
Bit 15 in data area 2	543	543	543	
Bit 0 in command area	544	544	544	
Bit 1 in command area	545	545	545	
Bit 2 in command area	546	546	546	
Bit 3 in command area	547	547	547	
(Reserved)	548	548	548	Not available
(Reserved)	549	549	549	Not available
(Reserved)	550	550	550	Not available
(Reserved)	551	551	551	Not available
User input	552	552	552	
	:	:	:	
	559	591	623	
(System inputs)	560	592	624	
	:	:	:	Not available
	575	607	639	

Remote Register Input (RWr)

Signal name	I/O port No.		
	2 stations occupied 8 words	3 stations occupied 12 words	4 stations occupied 16 words
User input	4736 - 4751	4736 - 4751	4736 - 4751
	4752 - 4767	4752 - 4767	4752 - 4767
	4768 - 4783	4768 - 4783	4768 - 4783
	4784 - 4799	:	:
	4800 - 4815	:	:
	4816 - 4831	4880 - 4895	4944 - 4959
	4832 - 4847	4896 - 4911	4960 - 4975
	4848 - 4863	4912 - 4927	4976 - 4991

Output Data (CC-Link remote device → Master)

Remote Output (RY)

Signal name	I/O port No.			Note
	2 stations occupied 64 points	3 stations occupied 96 points	4 stations occupied 128 points	
(-)	768	768	768	Not available
Robot running	769	769	769	
Robot error	770	770	770	
Servo ON	771	771	771	
Robot initialization completed	772	772	772	
Auto mode	773	773	773	
External mode	774	774	774	
Battery warning	775	775	775	
Robot warning	776	776	776	
Continued start permitted	777	777	777	
SS mode output	778	778	778	
(Reserved)	779	779	779	Not available
(Reserved)	780	780	780	Not available
(Reserved)	781	781	781	Not available
Command processing completed	782	782	782	
Status area odd parity	783	783	783	
Bit 0 in status area	784	784	784	
Bit 1 in status area	785	785	785	
Bit 2 in status area	786	786	786	
Bit 3 in status area	787	787	787	
Bit 4 in status area	788	788	788	
Bit 5 in status area	789	789	789	
Bit 6 in status area	790	790	790	
Bit 7 in status area	791	791	791	
Bit 8 in status area	792	792	792	
Bit 9 in status area	793	793	793	
Bit 10 in status area	794	794	794	
Bit 11 in status area	795	795	795	
Bit 12 in status area	796	796	796	
Bit 13 in status area	797	797	797	
Bit 14 in status area	798	798	798	
Bit 15 in status area	799	799	799	
User output	800 : 815	800 : 847	800 : 879	
(System output)	816 : 825	848 : 857	880 : 889	Not available
Error status flag	826	858	890	Synchronize with a robot error (I/O port No.770) or a robot warning (I/O port No.776).
Remote station ready	827	859	891	Synchronize with the robot initialized (I/O port No.772).
(System output)	828 : 831	860 : 863	892 : 895	Not available

Remote Register Output (RWw)

Signal name	I/O port No.		
	2 stations occupied 8 words	3 stations occupied 12 words	4 stations occupied 16 words
User output	8512 - 8527	8512 - 8527	8512 - 8527
	8528 - 8543	8528 - 8543	8528 - 8543
	8544 - 8559	8544 - 8559	8544 - 8559
	8560 - 8575	:	:
	8576 - 8591	:	:
	8592 - 8607	8656 - 8671	8720 - 8735
	8608 - 8623	8672 - 8687	8736 - 8751
	8624 - 8639	8688 - 8703	8752 - 8767