

Input Data (Master → CC-Link remote device)

Remote Input (RX)

Signal name	I/O port No.			Note
	2 stations occupied 384 points	3 stations occupied 640 points	4 stations occupied 896 points	
Step stop (all tasks)	512	512	512	
(Reserved)	513	513	513	Not available
Halt (all tasks)	514	514	514	
Strobe signal	515	515	515	
Skip interrupt	516	516	516	
(-)	517	517	517	Not available
(-)	518	518	518	Not available
Command and data odd parity	519	519	519	
Bit 0 in data area 1	520	520	520	
Bit 1 in data area 1	521	521	521	
Bit 2 in data area 1	522	522	522	
Bit 3 in data area 1	523	523	523	
Bit 4 in data area 1	524	524	524	
Bit 5 in data area 1	525	525	525	
Bit 6 in data area 1	526	526	526	
Bit 7 in data area 1	527	527	527	
Bit 0 in data area 2	528	528	528	
Bit 1 in data area 2	529	529	529	
Bit 2 in data area 2	530	530	530	
Bit 3 in data area 2	531	531	531	
Bit 4 in data area 2	532	532	532	
Bit 5 in data area 2	533	533	533	
Bit 6 in data area 2	534	534	534	
Bit 7 in data area 2	535	535	535	
Bit 8 in data area 2	536	536	536	
Bit 9 in data area 2	537	537	537	
Bit 10 in data area 2	538	538	538	
Bit 11 in data area 2	539	539	539	
Bit 12 in data area 2	540	540	540	
Bit 13 in data area 2	541	541	541	
Bit 14 in data area 2	542	542	542	
Bit 15 in data area 2	543	543	543	
Bit 0 in command area	544	544	544	
Bit 1 in command area	545	545	545	
Bit 2 in command area	546	546	546	
Bit 3 in command area	547	547	547	
(Reserved)	548	548	548	Not available
(Reserved)	549	549	549	Not available
(Reserved)	550	550	550	Not available
(Reserved)	551	551	551	Not available
User input	552	552	552	
	⋮	⋮	⋮	
	767	767	767	
	4096	4096	4096	
(System inputs)	⋮	⋮	⋮	
	4207	4463	4719	
	4208	4464	4720	
	⋮	⋮	⋮	Not available
	4223	4479	4735	

Remote Register Input (RWr)

Signal name	I/O port No.		
	2 stations occupied 64 words	3 stations occupied 96 words	4 stations occupied 128 words
User input	4736 - 4751	4736 - 4751	4736 - 4751
	4752 - 4927	4752 - 4767	4752 - 4767
	4768 - 4943	4768 - 4783	4768 - 4783
	⋮	⋮	⋮
	⋮	⋮	⋮
	5712 - 5727	6224 - 6239	6736 - 6751
	5728 - 5743	6240 - 6255	6752 - 6767
	5744 - 5759	6256 - 6271	6768 - 6783